G GLENSOUND ELECTRONICS LTD OPERATING INSTRUCTIONS	26-05-2009 File WP08-03B Issue 1

GS1U-050B ISDN UNIT FOR USE AS STUDIO TBU

GENERAL This equipment is controlled by a combination of using the front panel Keypad, the supplied Interquartz handset & the hold loops on the rear panel D9 connector.

CODEC SELECTION This unit houses 2 completely independent Codecs. A 3 position front panel toggle switch determines which of the 2 Codecs the keypad will control. The centre position of this toggle switch is a 'safe' position which disables the keypad.

HANDSET The supplied Interquartz handset provides off air talkback facilities to the incoming call. Like the front panel keypad the handset is only able to communicate to the codec that the front panel toggle switch has selected. If the guard time (see software setup) is set to long then lifting the handset will answer an incoming call. If the guard time is set to short then lifting the handset will answer an incoming call or dial an outgoing call (last number redial).

MONITORING A front panel loudspeaker is used for monitoring the functions of the 2 codecs. If this loudspeaker is muted (or the volume turned fully down) then monitoring can still take place on the handset.

ENTER SETUP To enter the setup menu it is necessary to hold the grey 'set up' button for a few seconds.

CONFIG Once in the setup menu it is only necessary to listen to the instructions. It is, at this stage, possible to directly enter a particular configuration if you know the correct number to insert.

LEAVE SETUP To leave the setup press the red 'CLEAR' button.

DIALLING It is now only necessary to enter the number you require terminated with the green 'DIAL' button. Hold the 'DIAL' button until the dialling is confirmed.

DIALLING MEMORIES First enter '#' followed by the two digit memory number. Then press and hold the 'DIAL' button until the dialling is confirmed

HANG-UP To hang up press thered 'CLEAR' button. For safety, if a call is in progress, it is necessary to hold the 'CLEAR' button for several seconds.

RE-DIAL To redial the last number called just press the 'DIAL' button.

QUERY At any time if you press the yellow '?' button the GS1U-050 will inform you of its present condition. For safety, if a call is in progress, it is necessary to hold the '?' button for several seconds before the GS1U-050 replies.